

CHERRY G80-3000

Accurate and reliable even after years of service



Models may vary from the image shown

FUNCTION AND PERFORMANCE

- Individual keys with Gold Crosspoint contacts (MX technology)
- Designed for continuous usage - over 50 mill. confirmations per key
- Robust and reliable
- Space-saving and ergonomic
- Ideal for limited space and 19" applications
- Can be used with the standard drivers of the operating system
- USB keyboard: the following keys can be programmed freely using KeyM@n software (software macros): function keys 'F1'-'F12', 'INSERT', 'DELETE', 'POSITION1', 'END', 'PAGE-UP', 'PAGE-DOWN', 'PRINT', 'PAUSE', 'ROLL', comma and zero in the numeric field.

TECHNICAL DATA

Weight main product:	33 oz
Dimensions product without packaging:	18,5 in x 7,68 in x 1,73 in
Weight of product incl. packaging:	40.57 oz
Dimensions product incl. packaging:	19,69 in x 10,04 in x 1,97 in
Content of master carton (pieces):	45
Cable-length:	5.74 ft
Storage temperature:	-4 °F - 140 °F
Working temperature:	32 °F - 122 °F
Product approvals:	<ul style="list-style-type: none">• BSMI• CE• cURus• FCC• UKCA• China RoHS• VDE
System	USB-A
Requirements-Hardware:	
Operating system:	<ul style="list-style-type: none">• Windows 7• Windows 8• Windows 10• Windows 11
Scope of delivery:	<ul style="list-style-type: none">• Keyboard• USB to PS/2 adapter• Short Manual
Reliability:	MTBF > 80.000 Stunden MCBF > 10 Mrd. Betätigungen
Service life per key (in million strokes):	50 mio. actuations
Max. current consumption (mA) of keyboard:	500 mA
Keyboard format:	Full-size (100%)

Integrated metal plate:	no
Anti-ghosting:	yes
Key encryption:	no
Internal memory:	no
Key labeling:	Laser etching + UV coating
Palm rest:	Palm rest not available
USB hub:	no
Adjustable feet:	integrated

Status LEDs:	no
Key technology:	Mechanical
Keycap material:	POM
Model number:	MX3000
Convenient exchange:	no
Warranty:	2 years warranty

Errors, technical changes and delivery options reserved. Technical information refers only to the specification of the products. Properties are not guaranteed.

EAN & Part number	Switches	Color	Illumination	Layout
4025112058547 G80-3000LPCDE-2	CHERRY MX BLACK	black	no	DE (Germany)
4025112058578 G80-3000LPCES-2	CHERRY MX BLACK	black	no	ES (Spain)
4025112061073 G80-3000LPCEU-2	CHERRY MX BLACK	black	no	EU (USA+ €-Symbol)
G80-3000LPCEU-2-	CHERRY MX BLACK	black	no	EU (USA+ €-Symbol)
4025112061646 G80-3000LPCGB-2	CHERRY MX BLACK	black	no	GB (United Kingdom)
4025112088773 G80-3000LPCKR-2	CHERRY MX BLACK	black	no	KR (Korea)
4025112061127 G80-3000LPCXX-2	CHERRY MX BLACK	black	no	XX (unprinted)
4025112061134 G80-3000LPCXY-2	CHERRY MX BLACK	black	no	
4025112063381 G80-3000LSCDE-2	CHERRY MX BLUE	black	no	DE (Germany)
4025112067020 G80-3000LSCEU-2	CHERRY MX BLUE	black	no	EU (USA+ €-Symbol)
4025112066290 G80-3000LSCGB-2	CHERRY MX BLUE	black	no	GB (United Kingdom)
G80-3000LSCRC-2	CHERRY MX BLUE	black	no	RC (English (US) / Chinese)
4025112067808 G80-3000LXCEU-2	CHERRY MX BROWN	black	no	EU (USA+ €-Symbol)
4025112076121	CHERRY MX BLACK	light-grey	no	CD (Canada)
4025112058530 G80-3000LPCDE-0	CHERRY MX BLACK	light-grey	no	DE (Germany)
4025112058561 G80-3000LPCES-0	CHERRY MX BLACK	light-grey	no	ES (Spain)
4025112058585 G80-3000LPCEU-0	CHERRY MX BLACK	light-grey	no	EU (USA+ €-Symbol)
4025112058592 G80-3000LPCFR-0	CHERRY MX BLACK	light-grey	no	FR (France)

EAN & Part number	Switches	Color	Illumination	Layout
4025112058608 G80-3000LPCGB-0	CHERRY MX BLACK	light-grey	no	GB (United Kingdom)
4025112092992 G80-3000LPCKR-0	CHERRY MX BLACK	light-grey	no	KR (Korea)
G80-3000LPCRB-0	CHERRY MX BLACK	light-grey	no	
4025112076145 G80-3000LPCRC-0	CHERRY MX BLACK	light-grey	no	RC (English (US) / Chinese)
4025112061813 G80-3000LPCXX-0	CHERRY MX BLACK	light-grey	no	XX (unprinted)
4025112058660 G80-3000LSCDE-0	CHERRY MX BLUE	light-grey	no	DE (Germany)
4025112058677 G80-3000LSCEU-0	CHERRY MX BLUE	light-grey	no	EU (USA+ €-Symbol)
4025112058684 G80-3000LSCGB-0	CHERRY MX BLUE	light-grey	no	GB (United Kingdom)
4025112061806 G80-3000LXCEU-0	CHERRY MX BROWN	light-grey	no	EU (USA+ €-Symbol)

Please contact your local CHERRY service and support teams or your CHERRY sales partners for versions available in your country.